

Queensland Digital Group Inc

814/815 Back to Back cable

6 March 1999

Link Radio to be re-wired to QDG packet standard

8 Pin	Link Radio	SK Cable	6 Pin	814/815
1	Sq	Green	3	PTT
2	Rx Audio	White	4	Tx Audio
3	Tx Audio	Black	1	Rx Audio
4	N/A			
5	PTT	Red	5	Squelch
6	N/A			
7	Ground	Orange / Yellow	6 & 2	Ground
8	+Vcc			

```

7 ^ 6
3 8 1
5 4
2

```

```

5 ^ 1
6
4 2
3

```

Solder side of plug

QDG Standard – Link Radio	
1	Squelch
2	Rx Audio
3	Tx Audio
4	
5	PTT
6	
7	Ground
8	+Vcc

SK1 – 814 / 815	
1	Rx Audio
2	Rx Audio
3	PTT
4	Tx Audio
5	Squelch
6	Ground

Remove R79 (47 ohm) from T3 board in 814 / 815

Copyright Queensland Digital Group Inc. 1999